

## Tronix Explorer 500Li 115V/60Hz (North American Socket Model)



The all-new Tronix Explorer 500Li is a Pure Sine Wave Inverter can seamlessly power multiple bi-voltage/digital/analog flash units or monolights, even set at full power. It is rated at 500watts continuous and powered by LiFePO4 Li-ion battery.

Rating: Not Rated Yet

**Price:**

Sales price: \$690.00

[Ask a question about this product](#)

### Description



The all-new Tronix Explorer 500Li is a Pure Sine Wave Inverter can seamlessly power multiple bi-voltage/digital/analog flash units or monolights, even set at full power.

Tronix Explorer 500Li is rated at 500watts continuous and recommended up to 2400ws. It is powered by LiFePO4 Li-ion battery. It can provide around 350 flashes using a 400ws monolight (ref: Elinchrom DliteIT 4), or around 700 flashes with a spare battery and at recycling time close to that of the wall socket.

At 4.7 kg (around 10 lbs, battery pack and built-in charger included), this very portable power supply comes with a carrying case for easier handling during on-location photo shoots and offers increased protection against dust, dirt, drips, etc. For extended photo shoots, Tronix Explorer 500Li has an easily-replaceable battery feature for quick installation of spare battery, allowing more chances to get that perfect shot. Powering computer peripherals and laptops or recharging gadgets such as smartphones are additional capabilities.

The output voltage of this Tronix Explorer 500Li model is 115V/60Hz.

This unit is compatible for countries on 100-120V, such as USA, Canada, Japan, etc.

Product Contents: 1-pc Tronix Explorer 500Li Main Inverter Unit, 1-pc Li-ion battery pack, 1-pc charging cord, 1-inverter carrying case, 1-battery

pack pouch

#### Performance Overview:

- @200ws flash, 700+ of pops
- @400ws flash, 350+ pops
- @500ws flash, 300+ pops

For more info on Tronix Explorer products, click [here](#).

On buying any Tronix products, customers enjoy the 30-day satisfaction guarantee where they can return the product if they are not satisfied with their purchase for a full refund and a one-year warranty, where customers can return the product for repair service or replacement. For more info on product warranty, click [here](#).

## Demo Video

## Specifications

### OUTPUT

- Output Voltage (Model Designation): 115V/60Hz
- Power Output/Power Capacity: 500watts
- Waveform: Pure sine wave
- Sockets: NEMA (x2)

### INPUT

- AC Input: 90Vac to 240Vac
- Type: LiFePO4 Li-ion battery
- Voltage: 12V
- Capacity: 90 Whr
- Charging Time: 4 to 6 hours

### INDICATORS

- Visual: Green LED for charging status

### PHYSICAL

- Dimensions: 16cm x 17.5cm x 21.5cm
- Net Weight: 4.7 kg (with battery)
- Gross Weight: 8 kg (including inverter and battery packaging and carrying case)

## Downloads

Download User's Guide

Download [Compatibility Chart](#)

Download Replacement Battery Data Sheet

## Accessories

- Power Cord: One (1) piece, two round pin , EU compatible
- Carry Case: INCLUDED

## Where to Buy

To purchase products locally, we recommend these Authorized Distributors and Dealers. For Distributors, please ask for their dealers.

For the complete list of distributors and dealers worldwide, click [here](#).